

QXD 1RU Firmware Release Notes



v1.0.0.2

Added

Web audio control

- New top-level Audio section with Inputs, Mix Bus, Zones and Outputs tabs, each with channel overview cards and per-channel detail pages.
- Live control of input gain/trim and sensitivity, zone level and source, and output level, mute, polarity, delay, crossover, limiter and speaker preset.
- Editable numeric fields alongside every slider, with range validation.
- Delay entry in milliseconds or metres, with a unit toggle.
- User-assignable names (up to 23 characters) for analogue inputs, digital inputs, mix buses, zones and outputs.
- Speaker preset selector on each output channel, including selecting FLAT to bypass.

Parametric EQ

- Browser-based parametric EQ with an interactive frequency-response chart and draggable band handles.
- 5 bands per analogue input, 10 bands per output.
- Copy EQ from one output channel to another.
- Compact mobile layout with a dot band selector, inline enable/type controls and a logarithmic Q slider.
- EQ settings are persisted and restored on boot, and are included in configuration backups.

Mix buses and output routing

- Four mix buses, each with eight independent source levels (32 mix points), configured from the Mix Bus tab.
- New Output Routing settings page for selecting the source of each of the four expansion outputs from any analogue input, digital input, mix bus or zone.

Metering

- Real-time level meters on the Inputs, Zones and Outputs pages and on the Dashboard.
- New zone (area) meters, read directly from the DSP, shown in a 2x2 dashboard grid and bridge-aware on outputs.
- Meters referenced to 0 dBFS peak.
- Analogue-VU style bar ballistics with a separate peak-hold line.
- Meter data broadcast at 5 Hz (200 ms) carrying a 250 ms peak maximum.
- Meter bar colour now reflects peak level.

Front panel

- Front panel lock with a 4-digit PIN: Set PIN, Clear PIN, Lock Now, and an auto-lock timeout (off, 30 s, 1 min, 5 min, 15 min, 30 min, 1 hr) based on encoder inactivity.
- Alert reason codes so the panel shows a specific message for PIN mismatch, wrong PIN and ?no PIN set? instead of a generic alert.
- Output mute added to the front panel output menu.
- Reset Advanced menu option for inputs, zones and outputs ? flattens EQ and clears advanced settings ? plus an indicator showing when a channel has advanced settings applied.
- Chunked speaker-library transfer to the front panel, so large libraries transfer reliably.

Configuration backup and restore

- GET /api/v1/config/backup downloads the complete device configuration as userConfig.bin.

QXD 1RU Firmware Release Notes



- POST `/api/v1/config/restore` accepts a configuration file, validates it, commits it atomically and restarts the device. Invalid or future-version files are rejected without touching the live config.
- Backup and restore are exposed in the web interface.

Control API

- REST GET endpoints: `/audio/inputs`, `/audio/outputs`, `/audio/zones`, `/audio/mixes`, `/audio/inputs/eq`, `/audio/outputs/eq`, `/settings/outputRouting`, `/settings/generator`.
- REST PATCH endpoints under `/api/v1/audio/` for input channels, output channels, zones, mix buses, individual EQ bands (`/eq/{band}`), individual mix levels (`/mixes/{m}/levels/{i}`) and expansion outputs. Omitted fields are left unchanged; unknown fields cause the whole request to be rejected.
- WebSocket command protocol (`t:"c"`) covering the same operations, with per-command success/error responses and targeted change broadcasts.
- Change broadcasts are scoped by topic (`audio.inputs`, `audio.outputs.eq`, `audio.zones`, `audio.mixes`, `audio.expansion`, `audio.settings`) and, for EQ, by channel ? a single EQ edit now sends roughly a quarter of the previous payload.
- New `/api/v1/speaker-library/commit` and `/api/v1/speaker-library/cancel` endpoints for two-phase library uploads.

Interface

- Light and dark themes with a toggle, and a redesigned visual style across the interface.
- Device name shown in the browser tab title.
- Signal generator controls (source, frequency, level, white noise) on the Inputs page.
- Fan curve selection on the Device > Setup page, backed by GET/POST `/api/v1/settings/fan`.
- Upload progress and processing feedback during speaker-library uploads.

Changed Behaviour

- Speaker-library metadata responses are now streamed, removing the previous size limit and keeping memory use constant regardless of library size.
- Speaker library format V3 stores FIR coefficients in natural order (`h[0]` first). V1 and V2 libraries are still supported and converted when loaded.
- Speaker-library uploads are now two-phase: presets are re-applied automatically once the new library is committed.
- Fan curve control moved from the WebSocket protocol to a REST endpoint.
- The expansion output endpoint moved to `/settings/outputRouting`.
- Slider commands are throttled to prevent flooding the device's WebSocket connection.
- WebSocket keep-alive heartbeat behaviour reworked for more reliable connection detection.
- Input gain trim levels adjusted (28 dBu, 10 dBV, 12 dBu).
- Mute and standby timers are shown prominently with a monospace readout.
- esp-mdns updated to 1.11.1, esp-dns updated.
- Configuration format bumped from v6 to v8, adding advanced-active flags, channel names, expansion output sources, front-panel lock state and zone priority storage.

Bug Fixes

DSP and audio

- FIR coefficients are now written to the DSP in the correct tap order. Previously they were written reversed. Existing

QXD 1RU Firmware Release Notes



configurations and libraries are migrated on load.

- Low-pass and high-pass EQ bands are now unity gain, the notch filter is a correct RBJ notch, and an invalid coefficient set now falls back safely instead of producing undefined output.
- Fixed the 180° all-pass filter.
- Corrected the DSP chain order so input metering is taken from the correct point.
- Meters are now referenced to 0 dBFS peak (previously mis-scaled), and a double division by 100 in the meter path was removed.
- Fixed crossover settings not being applied when a preset was recalled.
- Crossover filter type list corrected to the 14 types supported by the DSP.
- Input sensitivity labels corrected to match the DSP values (+12 / +28 / +4 dBu, ?10 dBV).
- Output source now uses the correct DSP enum, fixing an unhandled routing case.
- Filter enable and delay maximum parameter bugs fixed.

Stability

- Fixed occasional crashes when multiple WebSocket clients were connected and EQ was being adjusted.
- Fixed a race condition when copying EQ between channels.
- Fixed speaker-library file upload failures and chunked transfer errors on large files.

Power, GPIO and front panel

- Eco standby now wakes on audio as intended.
- GPIO mute now only auto-unmutes when the mute was triggered by GPIO, respects a user-set mute after a speaker preset is applied, and clears a stale mute flag on power-on.
- Fan speed is reset to 0 on boot to clear stale front-panel MCU state.
- Fixed front-panel display resets and menu wipes caused by sending zeroed display state.
- Reset Advanced now executes at the correct menu level.
- Front-panel changes are broadcast to connected browsers whenever the configuration changes.

Interface

- Bridge availability is no longer lost when a WebSocket update arrives.
- Power mode labels corrected ? Trigger and Trigger (Eco) were swapped relative to the firmware.
- Speaker preset selector now allows FLAT (UUID 0) and shows the current selection.
- Levels display ?? dB instead of -Infinity; the input ?Gain? control is now labelled ?Trim?.
- Power sliders show their current value and no longer apply a conflicting colour override.
- Scrollbars removed on 1RU displays; EQ canvas overflow fixed; EQ gridlines are now visible in both light and dark themes.
- Factory reset now preserves the package version across the NVS erase.

Package Versions

Core - V1.0.0.1

Aux - V0.0.2.9

Panel - V0.0.4.15

QXD 1RU Firmware Release Notes



v0.1.5.1

Package Contains the Following Updated Versions:

Core - v0.1.5.1

- Standardised Error Messages for Incorrect File Types

Package Contains the Following Maintained Versions:

Front Panel - v0.0.3.2

- Support for tree style speaker libraries
- Display of Firmware Update

Aux - v0.0.2.6

- Fix to Temperature Sensing

Known Issues

- No feedback for update progress. The amplifier will reboot upon completion of update.

** After update to this firmware version the device will show update progress for subsequent updates **

QXD 1RU Firmware Release Notes



v0.1.1.1

Package Contains the Following Updated Versions:

Core - v0.1.2.10

- Allow removal of Wi-Fi client details.
- Fixes to updating status information

Panel - v0.0.2.0

- Add display refresh for Network Info

Package Contains the Following Maintained Versions:

Aux - v0.0.2.6

- Fix to Temperature Sensing

Known Issues

- No feedback for update progress. The amplifier will reboot upon completion of update.

QXD 1RU Firmware Release Notes



v0.1.0.5

Package Contains the Following Updated Versions:

Core - v0.1.1.5

- Updates to API for Ethernet Settings

Package Contains the Following Maintained Versions:

Aux - v0.0.2.6

- Fix to Temperature Sensing

Panel - v0.0.1.2

- Fix to handling library to allow for larger libraries.

Known Issues

- No feedback for update progress. The amplifier will reboot upon completion of update.

QXD 1RU Firmware Release Notes



v0.1.0.2

Package Contains the Following Updated Versions:

Core - v0.1.1.3

- Introduce Static IP Addressing to WiFi Client and Ethernet Interfaces
- Code Tidying

Package Contains the Following Maintained Versions:

Aux - v0.0.2.6

- Fix to Temperature Sensing

Panel - v0.0.1.2

- Fix to handling library to allow for larger libraries.

Known Issues

- No feedback for update progress. The amplifier will reboot upon completion of update.

QXD 1RU Firmware Release Notes



v0.0.1.28

Package Contains the Following Versions:

Core - v0.1.0.20

- Fixed issue with Channel 1 Input Sensitivity Selection
- Improvements to Library Handling
- Bug fixes to Reset Handling
- Fix to Fan Speed

Aux - v0.0.2.6

- Fix to Temperature Sensing

Panel - v0.0.1.2

- Fix to handling library to allow for larger libraries.

Known Issues

- No feedback for update progress. The amplifier will reboot upon completion of update.